



Nice

C3-IP

Compact IP Power Management



Slim design, discrete installation
and maximum longevity

- Compact BlueBOLT™ Enabled Power Manager
- 3 Individually Controlled Outlets
- Protect-or-disconnect Surge Protection
- Standard EMI/RFI Filtration
- Over/Under Voltage Load Disconnect
- Power Sequencing
- 12A Capacity with circuit breaker
- Integrated Brackets for Wall Mounting



BlueBOLT™
Mobile

IP Power Management allows installers to monitor, control & program from any location.

Visit mybluebolt.com to create an account and download the BlueBOLT Mobile app.



C3-IP Compact IP Power Management

Features

- Ideal for entertaining systems (behind TVs), digital signage, and network equipment hubs
- Protects connected equipment for power surges and dangerous voltage conditions (3 outlets)
- Filters AC for best electronics performance
- Provides remote power, energy and network management for any web enabled device at www.mybluebot.com via the mobile
- Reduces visibility on energy usage with cloud-based monitoring and tracking
- Reduces excess energy consumption with scheduled on/off commands
- Automatically reboots network equipment when connectivity is lost

Specifications

AC Power	120Vac 50/60Hz
Total Outlets	3
Operating Control	Type 1
Total Current Capacity	12A Maximum
Rated Impulse Voltage	1500
Voltage Protection Rating (UL 1449)	L-N 500V
Initial Clamping Level	200V Peak, 141 Vrms
Energy Dissipation	1680 Joules
Peak Impulse Current	12,000
Protect-or-Disconnect	Yes

Over-Voltage Load Disconnect	140 Vac
Under-Voltage Load Disconnect	90 Vac
Filtration Technology	Standard RFI/EMI Filtration
Filtration Rating	10dB @ 10kHz, 17dB @ 30kHz, 33dB @ 100kHz, 55dB @ 1MHz
Thermal Fusing	Yes
Cord Length	0.5M IEC cord
Dimensions (LxWxH)	7.35" x 5.5" x 1.58"
Weight	2.6lbs
Temperature	0°C -+40°C (+32°F- +10°4F)
Operating Humidity	0-9% non-condensing
External Pollution Degree	Pollution Degree 2



Power Cord Port

Power Switch / Circuit Breaker

When switched off all outlets turn off immediately. When switch on, outlets turn back on in sequence. The power switch also acts as the circuit breaker. If the device is overloaded, the breaker will trip.

Outlet 1

Network Reset Button

Press using a safety pin, ball point pen, or other small object to reset connection to BlueBOLT cloud.

Network Connector

Connect an Ethernet cable (not provided) between the NETWORK port and an Internet router or modem with an established Internet connection for remote control and monitoring.



Outlet 2

Outlet 3

Ground Lug

Connect Panamax signal-line protection modules grounds to this terminal. Protect data lines as well as AC lines from surges is required for the connected equipment warranty.



Niceforyou.com

©2023 Nice North America LLC. All rights reserved.
All other products or name brands are trademarks of their respective holders.

